



COMPUTER SCIENCE

0478/12

Paper 1

October/November 2019

MARK SCHEME

Maximum Mark: 75

Published

This mark scheme is published as an aid to teachers and candidates, to indicate the requirements of the examination. It shows the basis on which Examiners were instructed to award marks. It does not indicate the details of the discussions that took place at an Examiners' meeting before marking began, which would have considered the acceptability of alternative answers.

Mark schemes should be read in conjunction with the question paper and the Principal Examiner Report for Teachers.

Cambridge International will not enter into discussions about these mark schemes.

Cambridge International is publishing the mark schemes for the October/November 2019 series for most Cambridge IGCSE™, Cambridge International A and AS Level components and some Cambridge O Level components.

bestexamhelp.com

This syllabus is regulated for use in England, Wales and Northern Ireland as a Cambridge International Level 1/Level 2 Certificate.

This document consists of **15** printed pages.

Generic Marking Principles

These general marking principles must be applied by all examiners when marking candidate answers. They should be applied alongside the specific content of the mark scheme or generic level descriptors for a question. Each question paper and mark scheme will also comply with these marking principles.

GENERIC MARKING PRINCIPLE 1:

Marks must be awarded in line with:

- the specific content of the mark scheme or the generic level descriptors for the question
- the specific skills defined in the mark scheme or in the generic level descriptors for the question
- the standard of response required by a candidate as exemplified by the standardisation scripts.

GENERIC MARKING PRINCIPLE 2:

Marks awarded are always **whole marks** (not half marks, or other fractions).

GENERIC MARKING PRINCIPLE 3:

Marks must be awarded **positively**:

- marks are awarded for correct/valid answers, as defined in the mark scheme. However, credit is given for valid answers which go beyond the scope of the syllabus and mark scheme, referring to your Team Leader as appropriate
- marks are awarded when candidates clearly demonstrate what they know and can do
- marks are not deducted for errors
- marks are not deducted for omissions
- answers should only be judged on the quality of spelling, punctuation and grammar when these features are specifically assessed by the question as indicated by the mark scheme. The meaning, however, should be unambiguous.

GENERIC MARKING PRINCIPLE 4:

Rules must be applied consistently e.g. in situations where candidates have not followed instructions or in the application of generic level descriptors.

GENERIC MARKING PRINCIPLE 5:

Marks should be awarded using the full range of marks defined in the mark scheme for the question (however; the use of the full mark range may be limited according to the quality of the candidate responses seen).

GENERIC MARKING PRINCIPLE 6:

Marks awarded are based solely on the requirements as defined in the mark scheme. Marks should not be awarded with grade thresholds or grade descriptors in mind.

Question	Answer	Marks															
1	<p data-bbox="286 252 685 284">One mark for each correct tick</p> <table border="1" data-bbox="286 319 954 679"><thead><tr><th data-bbox="286 319 757 416">Statement</th><th data-bbox="757 319 853 416">True (✓)</th><th data-bbox="853 319 954 416">False (✓)</th></tr></thead><tbody><tr><td data-bbox="286 416 757 483">25 kB is larger than 100 MB</td><td data-bbox="757 416 853 483"></td><td data-bbox="853 416 954 483">✓</td></tr><tr><td data-bbox="286 483 757 550">999 MB is larger than 50 GB</td><td data-bbox="757 483 853 550"></td><td data-bbox="853 483 954 550">✓</td></tr><tr><td data-bbox="286 550 757 617">3500 kB is smaller than 2 GB</td><td data-bbox="757 550 853 617">✓</td><td data-bbox="853 550 954 617"></td></tr><tr><td data-bbox="286 617 757 679">2350 bytes is smaller than 2 kB</td><td data-bbox="757 617 853 679"></td><td data-bbox="853 617 954 679">✓</td></tr></tbody></table>	Statement	True (✓)	False (✓)	25 kB is larger than 100 MB		✓	999 MB is larger than 50 GB		✓	3500 kB is smaller than 2 GB	✓		2350 bytes is smaller than 2 kB		✓	4
Statement	True (✓)	False (✓)															
25 kB is larger than 100 MB		✓															
999 MB is larger than 50 GB		✓															
3500 kB is smaller than 2 GB	✓																
2350 bytes is smaller than 2 kB		✓															

Question	Answer	Marks
2	<p>Four from:</p> <ul style="list-style-type: none"> • Arithmetic and logic unit (ALU) • Memory address register (MAR) • Memory data register (MDR) // Memory buffer register (MBR) • Accumulator (ACC) • Immediate Access Store (IAS) • Main memory // RAM • Program counter (PC) • Current instruction register (CIR) • Address bus • Data bus • Control bus • Input device • Output device • Secondary storage device 	4

Question	Answer	Marks
3(a)	<p>One from:</p> <ul style="list-style-type: none"> • Continuous data // by description • Non-discrete data // by description • By example, e.g. data such as a sound wave 	1
3(b)	<p>One from:</p> <ul style="list-style-type: none"> • <u>Discrete</u> data that has only two values • By example, e.g. binary data / 1's and 0's 	1

Question	Answer	Marks								
4(a)	• 52	1								
4(b)	<table border="1" style="display: inline-table; vertical-align: middle;"> <tr> <td style="text-align: center;">1</td> <td style="text-align: center;">1</td> <td style="text-align: center;">0</td> <td style="text-align: center;">1</td> <td style="text-align: center;">0</td> <td style="text-align: center;">0</td> <td style="text-align: center;">0</td> <td style="text-align: center;">0</td> </tr> </table>	1	1	0	1	0	0	0	0	1
1	1	0	1	0	0	0	0			
4(c)	• It is multiplied by 4	1								

Question	Answer	Marks
5(a)	<p>Four from:</p> <ul style="list-style-type: none"> • A compression algorithm is used • Discards any unnecessary sounds ... • ... using perceptual musical shaping • ... such as removing background noise / sounds humans can't hear // or other suitable example • Reduces sample size / resolution // by example • Reduces sample rate // by example • Sound is clipped • The data is permanently removed 	4
5(b)(i)	<p>One from:</p> <ul style="list-style-type: none"> • The file size will be smaller than lossless • Requires less storage space • Requires less time to transmit 	1
5(b)(ii)	<p>One from:</p> <ul style="list-style-type: none"> • The quality of the sound will be reduced • The original file cannot be restored 	1

Question	Answer	Marks
5(c)(i)	<p>Four from:</p> <ul style="list-style-type: none"> • Musical Instrument Digital Interface file • Stores a set of commands / instructions for how the sound should be played • Does not store the actual sounds • Data in the file has been recorded using digital instruments • Specifies pitch of the note // specifies the note to be played • Specifies when each note plays and stops playing // Specifies key on/off • Specifies duration of the note • Specifies volume of the note • Specifies the tempo • Specifies the type of instrument 	4
5(c)(ii)	<p>Four from:</p> <ul style="list-style-type: none"> • It uses a single wire ... • ... therefore, it is cheaper to manufacture / buy / install • ... therefore, less likely to have interference // no crosstalk • ... therefore, can be used over longer distances • Data is sent a bit at a time ... • ... therefore, less chance of data being skewed // data is received in order • Transmission can be synchronised ... • ... can reduce rate of errors 	4

Question	Answer			Marks																					
6	<p>One mark for each correct tick</p> <table border="1" data-bbox="286 319 1413 877"> <thead> <tr> <th data-bbox="286 319 1055 416">Statement</th> <th data-bbox="1055 319 1234 416">Resistive (✓)</th> <th data-bbox="1234 319 1413 416">Capacitive (✓)</th> </tr> </thead> <tbody> <tr> <td data-bbox="286 416 1055 483">This touch screen has multi-touch capabilities</td> <td data-bbox="1055 416 1234 483"></td> <td data-bbox="1234 416 1413 483">✓</td> </tr> <tr> <td data-bbox="286 483 1055 550">This touch screen cannot be used whilst wearing gloves</td> <td data-bbox="1055 483 1234 550"></td> <td data-bbox="1234 483 1413 550">✓</td> </tr> <tr> <td data-bbox="286 550 1055 647">This touch screen is made up of two layers with a small space in between</td> <td data-bbox="1055 550 1234 647">✓</td> <td data-bbox="1234 550 1413 647"></td> </tr> <tr> <td data-bbox="286 647 1055 745">This touch screen uses the electrical properties of the human body</td> <td data-bbox="1055 647 1234 745"></td> <td data-bbox="1234 647 1413 745">✓</td> </tr> <tr> <td data-bbox="286 745 1055 812">This touch screen is normally cheaper to manufacture</td> <td data-bbox="1055 745 1234 812">✓</td> <td data-bbox="1234 745 1413 812"></td> </tr> <tr> <td data-bbox="286 812 1055 877">This touch screen has a quicker response time</td> <td data-bbox="1055 812 1234 877"></td> <td data-bbox="1234 812 1413 877">✓</td> </tr> </tbody> </table>			Statement	Resistive (✓)	Capacitive (✓)	This touch screen has multi-touch capabilities		✓	This touch screen cannot be used whilst wearing gloves		✓	This touch screen is made up of two layers with a small space in between	✓		This touch screen uses the electrical properties of the human body		✓	This touch screen is normally cheaper to manufacture	✓		This touch screen has a quicker response time		✓	6
Statement	Resistive (✓)	Capacitive (✓)																							
This touch screen has multi-touch capabilities		✓																							
This touch screen cannot be used whilst wearing gloves		✓																							
This touch screen is made up of two layers with a small space in between	✓																								
This touch screen uses the electrical properties of the human body		✓																							
This touch screen is normally cheaper to manufacture	✓																								
This touch screen has a quicker response time		✓																							

Question	Answer	Marks
7(a)	<p>Four from:</p> <ul style="list-style-type: none"> • Membrane / matrix / circuit board present at base of keys • A key is pressed that presses a switch • When a key is pressed it completes a circuit // changes the current in a circuit • The location of the keypress is calculated • An index of characters is searched to find the corresponding keypress • Each character has an ASCII / Unicode value • The ASCII / Unicode value has a binary value • Keypress generates an interrupt • Each character / keypress is added to a buffer to wait to be processed • The binary can then be processed by the CPU to action the key press 	4
7(b)	<p>Three from:</p> <ul style="list-style-type: none"> • Display a web page • Sends a request to the web server • Receives data from web server • Translates HTML files • Processes client-side script, e.g. JavaScript • Store favourites • Store history • Navigation forward and backward • Check security • Store / access cookies • Find specific text within a web page • Downloading file from the web • Allows a homepage • Allows multiple tabs / web pages to be opened • Stores data in its cache 	3

Question	Answer	Marks
7(c)	<p>Three from:</p> <ul style="list-style-type: none"> • Hypertext Transfer Protocol Secure // It is a protocol ... • ... that is a set of rules/standards • Secure version of <u>HTTP</u> • Secure website // secures data • Uses TLS / SSL • Uses encryption 	3

Question	Answer	Marks
8(a)	<ul style="list-style-type: none"> • $X = 1$ if (A is 1 XOR C is 1) OR (B is 1 NAND C is NOT 1) • $X = (A \text{ XOR } C) \text{ OR } (B \text{ NAND NOTC})$ <p>One mark for each bullet:</p> <ul style="list-style-type: none"> • (A XOR C) • OR • (B NAND NOTC) 	3

Question	Answer	Marks																																													
8(b)	<p> Four marks for 8 correct outputs Three marks for 6 or 7 correct outputs Two marks for 4 or 5 correct outputs One mark for 2 or 3 correct outputs </p> <table border="1" data-bbox="286 419 1308 1010"> <thead> <tr> <th data-bbox="286 419 365 486">A</th> <th data-bbox="365 419 443 486">B</th> <th data-bbox="443 419 521 486">C</th> <th data-bbox="521 419 1234 486">Working space</th> <th data-bbox="1234 419 1308 486">X</th> </tr> </thead> <tbody> <tr> <td data-bbox="286 486 365 553">0</td> <td data-bbox="365 486 443 553">0</td> <td data-bbox="443 486 521 553">0</td> <td data-bbox="521 486 1234 553"></td> <td data-bbox="1234 486 1308 553">1</td> </tr> <tr> <td data-bbox="286 553 365 620">0</td> <td data-bbox="365 553 443 620">0</td> <td data-bbox="443 553 521 620">1</td> <td data-bbox="521 553 1234 620"></td> <td data-bbox="1234 553 1308 620">1</td> </tr> <tr> <td data-bbox="286 620 365 687">0</td> <td data-bbox="365 620 443 687">1</td> <td data-bbox="443 620 521 687">0</td> <td data-bbox="521 620 1234 687"></td> <td data-bbox="1234 620 1308 687">0</td> </tr> <tr> <td data-bbox="286 687 365 754">0</td> <td data-bbox="365 687 443 754">1</td> <td data-bbox="443 687 521 754">1</td> <td data-bbox="521 687 1234 754"></td> <td data-bbox="1234 687 1308 754">1</td> </tr> <tr> <td data-bbox="286 754 365 821">1</td> <td data-bbox="365 754 443 821">0</td> <td data-bbox="443 754 521 821">0</td> <td data-bbox="521 754 1234 821"></td> <td data-bbox="1234 754 1308 821">1</td> </tr> <tr> <td data-bbox="286 821 365 888">1</td> <td data-bbox="365 821 443 888">0</td> <td data-bbox="443 821 521 888">1</td> <td data-bbox="521 821 1234 888"></td> <td data-bbox="1234 821 1308 888">1</td> </tr> <tr> <td data-bbox="286 888 365 956">1</td> <td data-bbox="365 888 443 956">1</td> <td data-bbox="443 888 521 956">0</td> <td data-bbox="521 888 1234 956"></td> <td data-bbox="1234 888 1308 956">1</td> </tr> <tr> <td data-bbox="286 956 365 1010">1</td> <td data-bbox="365 956 443 1010">1</td> <td data-bbox="443 956 521 1010">1</td> <td data-bbox="521 956 1234 1010"></td> <td data-bbox="1234 956 1308 1010">1</td> </tr> </tbody> </table>	A	B	C	Working space	X	0	0	0		1	0	0	1		1	0	1	0		0	0	1	1		1	1	0	0		1	1	0	1		1	1	1	0		1	1	1	1		1	4
A	B	C	Working space	X																																											
0	0	0		1																																											
0	0	1		1																																											
0	1	0		0																																											
0	1	1		1																																											
1	0	0		1																																											
1	0	1		1																																											
1	1	0		1																																											
1	1	1		1																																											

Question	Answer	Marks																		
9(a)	<p>One mark per each correct tick</p> <table border="1" data-bbox="286 316 1357 730"> <thead> <tr> <th data-bbox="286 316 1016 384">Statement</th> <th data-bbox="1016 316 1187 384">True (✓)</th> <th data-bbox="1187 316 1357 384">False (✓)</th> </tr> </thead> <tbody> <tr> <td data-bbox="286 384 1016 453">Duplex data transmission can be either serial or parallel</td> <td data-bbox="1016 384 1187 453">✓</td> <td data-bbox="1187 384 1357 453"></td> </tr> <tr> <td data-bbox="286 453 1016 521">Duplex data transmission is when data is transmitted both ways, but only one way at a time</td> <td data-bbox="1016 453 1187 521"></td> <td data-bbox="1187 453 1357 521">✓</td> </tr> <tr> <td data-bbox="286 521 1016 590">Duplex data transmission is always used to connect a device to a computer</td> <td data-bbox="1016 521 1187 590"></td> <td data-bbox="1187 521 1357 590">✓</td> </tr> <tr> <td data-bbox="286 590 1016 659">Duplex data transmission is when data is transmitted both ways at the same time</td> <td data-bbox="1016 590 1187 659">✓</td> <td data-bbox="1187 590 1357 659"></td> </tr> <tr> <td data-bbox="286 659 1016 727">Duplex data transmission automatically detects any errors in data</td> <td data-bbox="1016 659 1187 727"></td> <td data-bbox="1187 659 1357 727">✓</td> </tr> </tbody> </table>	Statement	True (✓)	False (✓)	Duplex data transmission can be either serial or parallel	✓		Duplex data transmission is when data is transmitted both ways, but only one way at a time		✓	Duplex data transmission is always used to connect a device to a computer		✓	Duplex data transmission is when data is transmitted both ways at the same time	✓		Duplex data transmission automatically detects any errors in data		✓	5
Statement	True (✓)	False (✓)																		
Duplex data transmission can be either serial or parallel	✓																			
Duplex data transmission is when data is transmitted both ways, but only one way at a time		✓																		
Duplex data transmission is always used to connect a device to a computer		✓																		
Duplex data transmission is when data is transmitted both ways at the same time	✓																			
Duplex data transmission automatically detects any errors in data		✓																		
9(b)	<ul style="list-style-type: none"> • Parallel data transmission 	1																		

Question	Answer	Marks
9(c)	<p>Four from (maximum two marks per benefit):</p> <ul style="list-style-type: none"> • It is a universal standard ... • ... so it is likely to be compatible with the computer • It can only be inserted one way ... • ... so there is less chance of connecting a device incorrectly • It is a high-speed connection ... • ... so data will be transmitted quicker • It uses serial transmission ... • ... so it is cheaper to manufacture/buy • ... less chance of skewing / errors • It doesn't require a (wireless) network ... • ... therefore, can be used if a network is down • It is backwards compatible ... • ... so no additional technology is needed • It can power the device ... • ... therefore no separate source of power is needed • Drivers are automatically downloaded // device is automatically identified ... • ... so no need to find them online / install them manually 	4

Question	Answer	Marks
10(a)	<p>Four from:</p> <ul style="list-style-type: none"> • Validation method • Used to check data entry • Digit is calculated from data // by example • Digit is appended / added to data • Digit is recalculated when data has been input • Digits are compared • If digits are different, error is detected // If digits match, no error is detected 	4
10(b)	<p>Six from (maximum three marks per security method):</p> <ul style="list-style-type: none"> • Firewall ... • ... Monitors the traffic • ... Blocks any traffic that doesn't meet the criteria / rules • (Strong) password // biometric ... • ... Data cannot be accessed without the use of the password / bio data • ... Prevent brute force attacks • Encryption ... • ... Data will be scrambled • ... Key is required to decrypt the data • ... If data is stolen it will be meaningless • Physical security methods ... • ... The physical security will need to be overcome • ... This can help deter theft of the data • Antispyware ... • ... will remove any spyware from system • ... will prevent data being relayed to a third party 	6

Question	Answer	Marks
11(a)	RAM <ul style="list-style-type: none">• To store the data / instructions / parts of OS that are currently in use ROM <ul style="list-style-type: none">• To store the firmware / bootup instructions / BIOS SSD <ul style="list-style-type: none">• To store files / software // by example	3
11(b)	Two from: <ul style="list-style-type: none">• It is more durable // it has no moving parts• It has a faster read / write / access speed• It is more compact / light weight / smaller / portable• It uses less energy // battery will last longer• It is quieter• Not affected by magnetic forces• It runs at a cooler temperature• Less latency // takes less time to warm up	2