

Cambridge Assessment International Education

Cambridge International Advanced Subsidiary and Advanced Level

COMPUTER SCIENCE 9608/12

Paper 1 Written Paper

October/November 2017

MARK SCHEME
Maximum Mark: 75

Published

This mark scheme is published as an aid to teachers and candidates, to indicate the requirements of the examination. It shows the basis on which Examiners were instructed to award marks. It does not indicate the details of the discussions that took place at an Examiners' meeting before marking began, which would have considered the acceptability of alternative answers.

Mark schemes should be read in conjunction with the question paper and the Principal Examiner Report for Teachers.

Cambridge International will not enter into discussions about these mark schemes.


Cambridge International is publishing the mark schemes for the October/November 2017 series for most Cambridge IGCSE[®], Cambridge International A and AS Level components and some Cambridge O Level components.

® IGCSE is a registered trademark.



Question	Answer	Marks
1	Mark for stating the management task Mark for a corresponding description Maximum 2 marks for each task Maximum 3 tasks	6
	Process / Task Management Allocation of processor time Scheduling of processes or tasks / multi-tasking / multi-programming etc. By example – e.g. round-robin, shortest remaining time first etc. Resolution of conflict when two or more processes require the same resource Secondary Storage management Storage space divided into file allocation units Space allocated to particular files OS maintains a file directory and FAT	
	 Provides file naming conventions Controls access. Peripheral / Hardware / Device / Input/output Management Installation of appropriate driver software 	
	 Installation of appropriate driver software Controls access to data being sent to/from hardware/peripherals Controls access to hardware/peripherals Manages communication between devices / hardware and software 	
	 Provision of a User interface Allows user interaction with the computer system// Facilitates human computer communication Hides the complexity of the hardware from the user Or by example – e.g. GUI, command line etc. 	
	 Interrupt Handling Halts the execution of the current process Stores the values of the current process on the stack Loads and executes the appropriate ISR code Use of priorities for handling simultaneous interrupts Saves data on power outage 	
	Security Management Makes provision for recovery when data is lost Provides usernames and passwords / encryption / user accounts Prevents unauthorised access Ensures privacy of data	
	Provision of a software platform / environment On which other programs / applications can be run	

© UCLES 2017 Page 2 of 12



© UCLES 2017 Page 3 of 12

Question	Answer	Marks
3(a)(i)	 1 Mark per bullet, max 3 Security is keeping the data safe From accidental / malicious damage /loss By example of need for security Privacy is the need to restrict access to personal data To avoid it being seen by unauthorised people 	3
	By example of need for privacy	
3(a)(ii)	Mark for a suitable example For example: Personal data of students / staff	1
3(b)	Mark for stating the security measure Mark for a corresponding description Maximum 2 marks for each measure Maximum 2 measures	4
	 Physical measures Locked doors/keyboards etc. Secure methods of access, keypads/ biometric scans etc. 	
	 Backup of data Regular copies of the data are made If the data is corrupted it can be restored 	
	Disk-mirroring All activity is duplicated to a second disk in real time so that if the first disk fails there is a complete copy available	
	 Access rights Different access rights for individuals/groups of users To stop users editing data they are not permitted to access By example 	
	 Encryption If accessed, data cannot be understood by unauthorised personnel Accessed only by those with the decryption key 	
	Firewall To stop unauthorised access/hackers gaining access to the computer network	
	 Use authentication methods such as passwords and usernames Passwords should be strong / biometrics To prevent unauthorised access to data 	
	 Anti-malware program To detect / remove / quarantine viruses / key-loggers etc. Carrying out regular scans 	
	 Concurrent Access Controls // Record locking Closes a record to second user until first update complete To prevent simultaneous updates being lost 	

© UCLES 2017 Page 4 of 12

October/November 2017

Question	Answer	Marks
3(c)	1 Mark per bullet, max 2	2
	 Checking that the data entered matches / is consistent with that of the source. Comparison of two versions of the data Examples include double entry, visual checking, proof reading etc In the event of a mismatch – the user is forced to re-enter the data By example, e.g. creation of a password Does not check data is sensible/acceptable 	

© UCLES 2017 Page 5 of 12

Question	Answer	Marks
4(a)	1 Mark for each correct answer A – General purpose registers B – System clock C – ALU E – Control bus F – Address bus	5
4(b)	 1 Mark per bullet, max 2 The clock sends out a number of pulses in a given time interval (clock speed) Each processor instruction takes a certain number of clock cycles to execute The higher the clock frequency, the shorter the execution time for the instruction // Increasing the clock frequency improves performance 	2
4(c)(i)	 1 Mark per bullet Maximum 2 for Macro Maximum 2 for Directive Maximum 3 in total Macro • A group of instructions given a name // subroutine • A group of instructions that need to be executed several times within the same program • The statements are written once and called using the name whenever they need to be executed • Macro code is inserted into the source file at each place it is called • By example Directive • An instruction that directs the assembler to do something • A directive is not a program instruction • It is information for the assembler • By example 	3
4(c)(ii)	Mark for a suitable example For example: State the start address for the program //tell the assembler to set aside space for variables // include an external file etc.	1


© UCLES 2017 Page 6 of 12

Question				Answer	Marks
4(d)	Mark a	s shown			5
	ACC	Offset	OUTPUT		
		10			
	50		2		
	10				
	11	11		1 Mark for these two values, as first instructions	
	65			1 Mark for this value, in any row	
			Α	1 Mark for this value, in any row	
	11			1 Mark for this value, after 65, nothing in between	
	12	12		1 Mark for the rest	
	89		Υ		
	12				
	13	13			
	32				

© UCLES 2017 Page 7 of 12

Question		,	Answer		Marks	
4(e)	Mark as follows: Table entries: 1 Mark per bullet, max 4 EndProg 2 × Unknown 9 14 8 Numbering: 1 Mark per bullet, max 2 Relative address of Value is numbered 6 Number given for EndProg is next number in sequence to relative address of Value All numbers correct – award 2 marks					
		Symbolic address	Relative address			
		StartProg	0			
		Offset	UNKNOWN 9 1			
		Value	UNKNOWN 6 14			
		EndProg 7	UNKNOWN 8 8 9			

© UCLES 2017 Page 8 of 12



© UCLES 2017 Page 9 of 12

Question	Answer			
6(a)	1 mark for each correct row			
	Application Input device Output d	evice		
	Capture the text from a paper document, in order that the text can be word-processed Flatbed scanner / Digital camera			
	Producing a replica of a small plastic component from a washing machine 3D Prir	nter		
	A museum has interactive information facilities throughout the building Touch screen / touch pad / microphone etc. Touch screen / touch pad / speakers			
6(b)	 1 Mark per bullet to max 4 The hard disk has one or more platters made of aluminium or glass Each surface of the platter/disk is ferrous-oxide which is capable of being magnetised The platters/disks are mounted on a central spindle The disks are rotated at high-speed Each surface of the disk has a read/write head mounted on an arm positioned just above the surface Electronic circuits control the movement of the arm and hence the heads The surface of the platter/disk is divided into concentric tracks and sectors One track in one sector is the basic unit of storage called a block The data is encoded as a magnetic pattern for each block When writing to disk, a variation in the current in the head produces a variation in magnetic field on the disk When reading from disk, a variation in magnetic field produces a variation in current through the head 			

© UCLES 2017 Page 10 of 12

Question	Answer	Marks
7(a)(i)	1 Mark for correct primary key identified in both STAFF and CLIENT STAFF(StaffID, StaffName, Department) CLIENT(ClientName, Address, Town)	3
	1 Mark for correct primary key identified in VISIT VISIT(ClientName, VisitDate)	
	1 Mark for correct primary key identified in INTERVIEW INTERVIEW(ClientName, VisitDate, StaffID, SpecialistFocus, InterviewText)	
7(a)(ii)	1 Mark for each correct relationship	3
	CLIENT VISIT	
	VISIT INTERVIEW	
	INTERVIEW	
7(b)	1 Mark for correct answer	1
	Add attribute VisitReportText to table VISIT	
7(c)(i)	1 Mark for each correct line	3
	<pre>UPDATE CLIENT SET ClientName = 'Albright Holdings' WHERE ClientName = 'ABC Holdings';</pre>	
7(c)(ii)	1 Mark per bullet, max 2	2
	Referential integrity should be maintained // Referential integrity could be violated	
	Data becomes inconsistent	
	There may be records in the VISIT and INTERVIEW tables / other tables with client name ABC Holdings	
	The ClientName in the VISIT and INTERVIEW tables / other tables might not be automatically updated	
	Records in the VISIT and INTERVIEW tables / other tables will become orphaned	

© UCLES 2017 Page 11 of 12

Question	Answer	Marks
7(d)	1 Mark for each correct line	3
	SELECT StaffID FROM INTERVIEW WHERE ClientName = 'New Age Toys' AND VisitDate = '13/10/2016'; (Accept clauses other way round)	
7(e)	1 Mark for a correct answer Add a suitable attribute, for example, EuropeTraveller to the STAFF table // Add a suitable attribute, for example, Country to the CLIENT table	1

© UCLES 2017 Page 12 of 12